

| NuQ152 Bi-Amp |               |            |          |
|---------------|---------------|------------|----------|
| FILTER        | FREQUENCY(Hz) | Q/BW       | GAIN(dB) |
| LOW 15 inch   |               |            |          |
| HPF           | 39.2          | 24dB/oct   | BUT      |
| LPF           | 1730          | 24dB/oct   | L-R      |
| HiSHF         |               |            |          |
| LoSHF         |               |            |          |
| PEQ1          | 76.6          | 2.4/0.597  | 1.2      |
| PEQ2          | 86.3          | 3/0.279    | 1.2      |
| PEQ3          | 133           | 4.35/0.331 | -1.8     |
| PEQ4          | 270           | 2.4/0.597  | -3.4     |
| PEQ5          | 773           | 3/0.279    | -3.8     |
| PEQ6          | 1040          | 4.35/0.331 | -1.8     |
| DELAY         | 0.12 ms       |            |          |
| HIGH 1 inch   |               |            |          |
| HPF           | 1810          | 24dB/oct   | L-R      |
| LPF           |               |            |          |
| HiSHF         | 10300         | 12dB/oct   | 6.4      |
| LoSHF         |               |            |          |
| PEQ1          | 982           | 3.48/0.413 | -4.2     |
| PEQ2          | 2300          | 3.75/0.384 | -2.4     |
| PEQ3          | 4330          | 6.29/0.229 | -3.6     |
| PEQ4          | 5000          | 1.21/1.161 | -4       |
| PEQ5          | 10000         | 4.35/0.331 | -1.8     |
| PEQ6          | 18000         | 7.29/0.198 | -3.8     |
| DELAY         | NON           |            |          |